

## Claims

1. A system for driving a compressor, comprising  
an induction motor (2) for driving the compressor  
5 (3a), said induction motor including a squirrel cage  
rotor, and  
a controller (1) for controlling the induction  
motor, said controller comprising  
a memory (47) for storing drive patterns for driving  
10 the induction motor,  
a first frequency generation means (43) for  
generating a field frequency based on a field command  
and/or  
a second frequency generation means (44) for  
15 generating a voltage frequency based on a voltage  
command,  
wherein a drive pattern is extracted from the memory  
based on the generated frequency or frequencies.
- 20 2. The system according to claim 1, wherein the  
controller comprises a processing means (42) for  
generating the field command and/or the voltage command  
based on an input request.
- 25 3. The system according to claim 1, wherein the  
controller is adapted to distinguish between a steady  
state and a transient state of the induction motor.
4. The system according to claim 3, wherein the  
30 processing means (42) is adapted to generate the field  
command and/or the voltage command depending on the state  
of the induction motor.

- 26 -

5. The system according to claim 4, wherein the field command and/or voltage command is generated based on look-up tables.

5 6. The system according to claim 4, wherein the field command and/or voltage command is generated based on a model based control.

7. A system for driving a compressor, comprising  
10 an induction motor (2) for driving for driving the compressor (3a), said induction motor including a squirrel cage rotor, and  
a controller (1) for controlling the induction motor, wherein the controller is adapted to distinguish  
15 between a steady state and a transient state of the induction motor.

8. The system according to claim 7, wherein the controller is adapted to control the induction motor  
20 depending on the state of the induction motor.

9. The system according to claim 8, wherein the controller generates a field command and/or a voltage command dependent on the state of the induction motor.  
25

10. The system according to claim 9, wherein the field command and/or voltage command is generated based on look-up tables.

30 11. The system according to claim 9, wherein the field command and/or voltage command is generated based on a model based control.

12. The system according to claim 7, wherein the  
35 controller comprises

- 27 -

a memory (47) for storing drive patterns for the induction motor,

a first frequency generation means (43) for generating a field frequency based on a field command  
5 and/or

a second frequency generation means (44) for generating a voltage frequency based on a voltage command,

wherein a drive pattern is extracted from the memory  
10 based on the generated frequency or frequencies.

13. The system according to claim 12, wherein the controller comprises a processing means (42) for generating the field command and/or the voltage command  
15 based on an input request.

14. The system according to claim 1 or 12, wherein the first and/or the second frequency generation means (43, 44) is a voltage controlled oscillator.

20

15. The system according to claim 1 or 12, further comprising a counter (45, 46) receiving the frequency output of the frequency generation means (43, 44),

wherein the counter is adapted to count a value  
25 based on the frequency of the frequency generation means, and

the frequency is used as an address for accessing the memory (47).

30 16. The system according to claim 1 or 12, wherein the first frequency generation means (43) for generating the field frequency and the second frequency generation means (44) for generating a voltage frequency is used, wherein

- 28 -

the memory (47) is accessed by using a first address and a second address, and the system further comprises a first counter (45) and a second counter (46), wherein

5 the first counter is adapted to count a value based on the frequency of the first frequency generation means, and the second counter is adapted to count a value based on the frequency of the second frequency generation means, wherein

10 the count value of the first frequency generation means is used as the first address, and the count value of the second frequency generation means is used as a second address.

17. The system according to claim 16, wherein one of the 15 first and second addresses is a column address, and the other address of the first and second addresses is a line address.

18. The system according to any of the claims 1 to 17, 20 wherein the compressor (3a) is a part of a turbocharger (3).

19. The system according to any of the claims 1 to 17, 25 wherein the compressor is an electrically driven compressor.

20. The system according to any of the claims 1 to 17, wherein the compressor is part of an electrically assisted turbocharger.

30